

--	--	--	--	--	--	--	--	--	--



## P.E.S. College of Engineering, Mandya - 571 401

(An Autonomous Institution affiliated to VTU, Belgaum)

Fifth Semester, B.E. - Electronics and Communication Engineering

Semester End Examination; Dec - 2016/Jan - 2017

Digital Communication Theory

Time: 3 hrs

Max. Marks: 100

**Note:** Answer **FIVE** full questions, selecting **ONE** full question from each unit.

### UNIT - I

- 1 a. Define the following terms related to random process : 6
- i) Mean    ii) Correlation    iii) Covariance Function.
- b. A Random variable has a probability density function,
- $$f_x(x) = \begin{cases} \frac{5}{4}(1-x^4) & 0 \leq x \leq 1 \\ 0 & \text{elsewhere} \end{cases} \quad \text{Find;}$$
- 6
- i)  $E[X]$     ii)  $E[4X + 2]$     iii)  $E[X^2]$ .
- c. What is Gaussian process? Mention the properties of Gaussian process. 8
- 2 a. Define and mention the properties of power spectral density. 10
- b. Let two random process  $X(t)$  and  $Y(t)$  be defined by;
- $$X(t) = A \cos \omega_0 t + B \sin \omega_0 t \quad Y(t) = B \cos \omega_0 t - A \sin \omega_0 t.$$
- Where, A & B are random variables assumed to have zero mean and are uncorrelated but 10
- A & B are assumed to have variances  $\sigma^2$ .
- Find the cross-correlation function  $R_{xy}(\tau)$ .

### UNIT - II

- 3 a. Explain the generation and re-construction of band-pass signal  $g(t)$ . 10
- b. Determine the Nyquist rate and the Nyquist sampling interval for the following signals and also plot the spectrum, 10
- i)  $g_1(t) = \sin c(100\pi t)$     ii)  $g_2(t) = \sin c^2(100\pi t)$
- iii)  $g_3(t) = \sin c(100\pi t) + \sin c(50\pi t)$ .
- 4 a. Discuss the concept of practical sample and hold circuit along with block diagram and spectrum of the output signals. 10
- b. A signal  $g(t) = 10 \cos(20\pi t) \cos(200\pi t)$  is sampled at the rate of 250 samples/second,
- i) Sketch the spectrum of the sampled signal 10
- ii) Specify the cutoff ideal reconstruction filter, so as to recover  $g(t)$  from  $g_s(t)$
- iii) Specify the Nyquist rate for the signal  $g(t)$ .

**UNIT - III**

- 5 a. Distinguish the characteristics of midtread and midriser quantizer along with variation of quantization error with input. 10
- b. Explain the processing gain of DPCM system. 4
- c. For a binary PCM signal, determine 'L', if the compression parameter  $\mu = 100$  and minimum  $[SNR]_0$ , dB = 45 dB. Determine the  $[SNR]_0$  in dB with this value of L. 6
- 6 a. A PCM system uses a uniform quantizer followed by a 7-bit encoder. The bit rate of the system is 50 M bits/sec.
  - (i) What is the message bandwidth for which the system operates satisfactorily? 10
  - (ii) Determine the output signal-to-quantizing noise ratio when a sinusoidal modulating wave of frequency 1 MHz is applied to the input.
- b. With a neat block diagram, explain adaptive sub-band coding scheme in Transmitter and receiver. 10

**UNIT - IV**

- 7 a. Sketch the encoded waveform for the bit stream 011011 for the following schemes,
  - i) RZ Uni-Polar ii) NRZ Uni-Polar iii) NRZ polar 10
  - iv) Biphasic v) NRZ bipolar.
- b. Explain adaptive equalizing filter for base band data transmission. 10
- 8 a. A multi-level digital communication system transmits one of the 16 possible levels over the channel every 0.8 ms. 6
  - i) What is the minimum number of bits corresponding to each level?
  - ii) What is the baud rate? iii) What is the bit rate?
- b. Show that power spectra of discrete PAM signal is  $S_x(f) = a^2 T_b \text{sinc}^2(f T_b)$ . 10
- c. Sketch and explain ISI. 4

**UNIT - V**

- 9 a. Derive probability of error for a coherent FSK system. 10
- b. With transmitter and receiver block diagram, explain coherent QPSK system. 10
- 10a. A binary data is transmitted using ASK over an AWGN channel at a rate 24 MBPS. The carrier amplitude at the receiver is 1 mV. Noise power spectral density,  $N_o/2 = 10^{-15} \text{ W/Hz}$ . 8

Find the average probability of error, if the detection is (i) Coherent (ii) Non-coherent.
- b. With necessary waveforms and block diagrams, explain continuous phase modulation scheme. 12

\* \* \*