



# P.E.S. College of Engineering, Mandya - 571 401

(An Autonomous Institution affiliated to VTU, Belagavi)

Sixth Semester, B.E. - Electrical and Electronics Engineering

Semester End Examination; July / Aug. - 2022

## Digital Signal Processing

Time: 3 hrs

Max. Marks: 100

### Course Outcomes

The Students will be able to:

CO1 – Apply the knowledge of DFT and FFT in its various applications.

CO2 – Transformation of digital signals into the frequency domain using FFT/DFT methods.

CO3 – Implementation or realization of different digital structures for IIR and FIR systems.

CO4 – Design and Implementation of IIR filters using Bilinear Transformation.

CO5 – Apply the knowledge of DSP Processor and its applications. Thermal energy conversion systems and applications.

**Note: I) PART - A** is compulsory. **Two** marks for each question.

**II) PART - B:** Answer any **Two** sub questions (from a, b, c) for a Maximum of **18 marks** from each unit.

Q. No.	Questions	Marks	BLs	COs	POs
<b>I : PART - A</b>		<b>10</b>			
I a.	State Linearity property.	2	L1	CO1	PO1
b.	List the similarities between DIT and DIF FFT algorithm.	2	L1	CO2	PO1
c.	What are the two types of digital filter?	2	L1	CO3	PO1
d.	What is rectangular window? Explain	2	L1	CO4	PO1
e.	List the application of DSP processors.	2	L1	CO5	PO1
<b>II : PART - B</b>		<b>90</b>			
<b>UNIT - I</b>		<b>18</b>			
1 a.	Find N-point DFT of the following sequences:				
	i) $x(n) = \cos\left(\frac{2\pi}{N}K_0n\right); 0 \leq n \leq N-1$	9	L3	CO1	PO2
	ii) $y(n) = \sin\left(\frac{2\pi}{N}K_0n\right); 0 \leq n \leq N-1$				
b.	State and Prove:				
	i) Circular time shift property	9	L3	CO1	PO2
	ii) Circular frequency property				
c.	Find circular convolution of two given sequence $x_1(n) = \{1, 2, 3, 1\}$ and $x_2(n) = \{4, 3, 2, 2\}$ using time domain approach and using frequency domain approach.	9	L3	CO1	PO2
<b>UNIT - II</b>		<b>18</b>			
2 a.	Develop a DIF FFT algorithm to compute N-point DFT $x(K)$ of an N-Point sequence $x(n)$ .	9	L3	CO2	PO3
b.	Given $x(n) = \{1, 2, 3, 4, 4, 3, 2, 1\}$ , find $x(K)$ using DIT FFT algorithm.	9	L3	CO2	PO3
c.	Obtain 8-point DFT of the following sequence using radix-2 DIF FFT algorithm. Show all the result along the signal flow graph, given $x(n) = \{2, 1, 2, 1\}$	9	L3	CO2	PO3

