



P.E.S. College of Engineering, Mandya - 571 401

(An Autonomous Institution affiliated to VTU, Belagavi)

Sixth Semester, B.E. - Electrical and Electronics Engineering

Semester End Examination; June - 2017

Electrical Machine Design

Time: 3 hrs

Max. Marks: 100

Note: i) Answer **FIVE** full questions, selecting **ONE** full question from each unit.

ii) Missing data may suitably assume.

iii) Design data handbook may be permitted.

UNIT - I

- | | | |
|-------|---|----|
| 1. a | What are the limitations involved in design of electrical machine? | 6 |
| | b. Define 'Specific magnetic loading' and specific electric loading. What are the advantages and disadvantages of using higher specific loadings? | 8 |
| | c. What are the electrical properties of insulating materials? Classify the insulating materials used in electrical machines according to their thermal stability in service. | 6 |
| 2. a. | Derive the output equation of a D.C. machine. | 6 |
| | b. What are the advantages and disadvantages of large number of poles in D.C. machine? | 4 |
| | c. Determine suitable values for; | |
| | i) External diameter of armature ii) Core length | |
| | iii) Number of poles, for a 1000 kW, 500 volts, 350 rpm, DC generator, justify the value of diameter and length of armature from the limiting value of peripheral speed and voltage between adjacent commutator segment respectively. | 10 |
| | Assume: Specific magnetic loading = 0.962, Specific electric loading = 40,000 | |

UNIT - II

- | | | |
|-------|---|----|
| 3. a. | Explain the factors which are considered when selecting the number of armature slots in D.C. machine. | 8 |
| | b. Design the lap wound armature winding for a 500 kW, 440 V, 375 rpm, 8 poles compound generator with external diameter of 1.1 m, gross armature length of 0.30 m and flux per pole of 0.0876 wb, Find the following details of winding: | 12 |
| | i) Number of armature conductors ii) Number of slots | |
| | iii) Size of armature conductors iv) Dimensions of slots. | |
| 4. a. | During the design of armature of a 250 kW, 400 V, 6 pole, 600 rpm, DC compound generator, following information has been obtained, | |
| | i) External diameter of armature 0.72 m | |
| | ii) Cross core length 0.25 m | 10 |
| | iii) Flux per pole, 0.0585 wb, based on the above design information. | |

- b. Determine the main dimensions, turns/phase, number of slots, conductor's cross section and slot area of a 250 HP, 3 ϕ , 50 Hz, 400 V, 1410 rpm, slipping Induction motor. Assume $B_{av} = 0.5$ T, $Q = 30,000$ Ac/m, $\eta = 0.9$ and pf = 0.9 winding factor is 0.955, current density is 3.5 A/mm². The slot space factor is 0.4 and ratio of core length to pole pitch is 1.2. 10
- 8 a. What is meant by the terms 'Crawling' and 'Cogging' in case of 3 phases Induction motors? What steps would you take in the design procedure, so as to minimize these tendencies? 10
- b. During the preliminary design of 270 kW, 3600 V, 3 phases, 8 poles, 50 Hz slipping Induction motor, star connected following information have been obtained.
- Gross length of stator = 0.38 m
- Internal diameter of stator = 0.67 m
- Outer diameter of stator = 0.86 m
- Number of stator slots = 96 10
- Number of conductor per slot = 12
- Based on the above information, determine the following design data's for this motor:
- i) Flux per pole ii) Gap density iii) Conductor size
- iv) Size of slot v) Copper losses.

UNIT - V

- 9 a. Define "Short Circuit Ratio" (SCR) for a synchronous generator. Explain affects of SCR on synchronous machine performance. 10
- b. A 500 kVA, 3.3 kV, 50 Hz, 600rpm, 3 ϕ alternator has 180 turns per phase. Estimate the length of air gap if the average flux density is 0.54 wb/m², the ratio of pole arc to pole pitch 0.65; the SCR 1.2, the gap contraction factor is 1.15 and the winding factor 0.955, The mmf required for gap is 80% of no load field mmf and the winding factor is 0.955. 10
- 10 a. Derive the output equation in terms of specific loadings for a synchronous machine. 10
- b The following is the design data available for a 1250 kVA, 3 phase, 50 Hz, 3300 V, Star connected, 300 rpm alternator of salient pole type; stator core diameter $D = 1.9$ m; stator core length $L = 0.335$ m, pole arc/pole pitch is 0.66; turns per phase is 150; single layer concentric winding with 5 conductor per slot, short circuit ratio is 1.2. Assume that the distribution of gap flux is rectangular under the pole arc with zero valves in the inter polar region calculate: 10
- i) Specific magnetic loading ii) Armature mmf per pole
- iii) Gap density over pole arc iv) Air gap length
- MMF required for air gap is 0.88 of no load field mmf and the gap contraction factor is 1.15.